

	1	2	3	4	5	6	7	8	9
A <b>Manufacturer</b>	CWT	CWT	CWT	CWT	CWT	APD	APD	APD	APD
B <b>address</b>	No. 222, Sec. 2, Nankan Rd., Lujhu Township, Taoyuan County 338, Taiwan	No. 222, Sec. 2, Nankan Rd., Lujhu Township, Taoyuan County 338, Taiwan	No. 222, Sec. 2, Nankan Rd., Lujhu Township, Taoyuan County 338, Taiwan	No. 222, Sec. 2, Nankan Rd., Lujhu Township, Taoyuan County 338, Taiwan	No. 222, Sec. 2, Nankan Rd., Lujhu Township, Taoyuan County 338, Taiwan	No.5,Lane 83,Lung-Sou St.,Taoyuan City 330,Taiwan	No.5,Lane 83,Lung-Sou St.,Taoyuan City 330,Taiwan	No.5,Lane 83,Lung-Sou St.,Taoyuan City 330,Taiwan	No.5,Lane 83,Lung-Sou St.,Taoyuan City 330,Taiwan
C <b>Model identifier</b>	2ABB012F UK	2ABB018F UK	2ABL025F UK	2ABL030F UK	2ABN036F UK	WA-12M12FG	WB-18D12FG	WA-24Q12FG	WA-36A12FG
	2ABB012F EU	2ABB018F EU	2ABL026F EU	2ABL030F EU	2ABN036F EU	WA-12M12FK	WB-18D12FK	WA-24Q12FK	WA-36A12FK
D <b>Input voltage</b>	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V	100~240V
E <b>Input AC frequency</b>	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz
<b>Output voltage DC</b>	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V	12.0V
F <b>Output current</b>	1.0A	1.5A	2.0A	2.5A	3.0A	1.0A	1.5A	2.0A	3.0A
G <b>Output power</b>	12.0W	18.0W	24.0W	30.0W	36.0W	12.0W	18.0W	24.0W	36.0W
H <b>Average active efficiency</b>	84.9%	86.2%	87.6%	87.8%	89.8%	83.7%	85.4%	88.6%	88.2%
I <b>Efficiency at low load 10 %</b>	73.6%	78.0%	81.3%	83.3%	83.7%	74.5%	80.5%	86.4%	85.4%
J <b>No-load power consumption</b>	0.07W	0.07W	0.07W	0.07W	0.07W	0.07W	0.10W	0.07W	0.10W

\* the external power supply used for each product will be model dependent.